

3U CompactPCI Extension Card Compatibility Matrix



	Supported Interfaces on Side Cards	F14 R00	F14 R01	F15 R00	F15 R01	F15 R02	F18 R00	F19P R00/R01	F21P R00/R01	F21P R02	F22P R02	F23P R00	F26L R00
F600	Side card installed on left side of CPU	-	-	-	-	-	-	-	-	-	-	-	-
R00/R01	Side card installed on right side of CPU	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Onboard HDD via SATA0	✓	✓	✓	✓	✓	✓	Only 1 SATA port supported by CPU board which can be switched in the CPU board's BIOS					✓
	External SATA device via SATA1	✓	✓	✓	✓	✓	✓						-
	COM on SA-Adapter via USB1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB3	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB4	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Mechanical kit for side card installation	Included in F600 delivery											
F601	Side card installed on left side of CPU	-	-	-	-	-	-	-	-	-	-	-	-
R00/R01	Side card installed on right side of CPU	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Onboard HDD via SATA1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	-
	COM on SA-Adapter via USB2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	PS/2 at front via USB3	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	RS485 at rear via USB4	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	HD Audio	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Primary DVI via SDVO B	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	-	-
	Secondary DVI via SDVO C	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				-
	Ethernet at rear via PCIe0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Mechanical kit for side card installation	Included in F601 delivery											

3U CompactPCI Extension Card Compatibility Matrix



	Supported Interfaces on Side Cards	F14 R00	F14 R01	F15 R00	F15 R01	F15 R02	F18 R00	F19P R00/R01	F21P R00/R01	F21P R02	F22P R02	F23P R00	F26L R00
F602 R00	Side card installed on left side of CPU	-	-	-	-	-	-	-	-	-	-	-	-
	Side card installed on right side of CPU	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Onboard HDD via SATA0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	USB at front via USB1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	DVI via SDVO B	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	-	-
	PCIe0 at rear	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	PCIe1 at rear	✓	✓	✓	✓	✓	✓	✓	✓	Supported on standard versions if PCIe 3 is not supported			✓
	PCIe2 at rear	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	-
	PCIe3 at rear	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board	Optional, can be supported on special board versions instead of PCIe 1			-
	Mechanical kit for side card installation	Included in F602 delivery											
F603 R00/R01	Side card installed on left side of CPU	Not supported by CPU board	✓	Not supported by CPU board	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Side card installed on right side of CPU	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Onboard HDD via SATA0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	USB at front via USB1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	USB at front via USB2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	CompactFlash via USB3	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	RS232 at front via USB4	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Mechanical kit for side card installation	Included in F603 delivery											

3U CompactPCI Extension Card Compatibility Matrix



	Supported Interfaces on Side Cards	F14 R00	F14 R01	F15 R00	F15 R01	F15 R02	F18 R00	F19P R00/R01	F21P R00/R01	F21P R02	F22P R02	F23P R00	F26L R00	
F605	Side card installed on left side of CPU	-	-	-	-	-	-	-	-	-	-	-	-	
	Side card installed on right side of CPU	Not supported by CPU board	✓	Not supported by CPU board	✓	✓	✓	✓	✓	✓	✓	✓	✓	
	Onboard HDD via SATA0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	
	PCIe0	PCIe-to-PCI bridge x4 or J15 XMC x4 connector or	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		J15 XMC x1 connector	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	PCIe1	PCIe-to-PCI bridge x4 or	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		J15 XMC x4 connector or	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		J15 XMC x1 connector	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	PCIe2	PCIe-to-PCI bridge x4 or	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		J15 XMC x4 connector	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
	PCIe3	PCIe-to-PCI bridge x4 or	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		J15 XMC x4 connector	✓	✓	✓	✓	✓	✓	✓	Not supported by CPU board				
		Mechanical kit for side card installation	Not included in F605 delivery											

3U CompactPCI Extension Card Compatibility Matrix



	Supported Interfaces on Side Cards	F14 R00	F14 R01	F15 R00	F15 R01	F15 R02	F18 R00	F19P R00/R01	F21P R00/R01	F21P R02	F22P R02	F23P R00	F26L R00
F606	Side card installed on left side of CPU	Not supported by CPU board	✓	Not supported by CPU board	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Side card installed on right side of CPU	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Onboard HDD via SATA0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	COM on SA-Adapter via USB2	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	USB on rear via USB3	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	USB on rear via USB4	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Gigabit Ethernet via PCIe 0	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Gigabit Ethernet via PCIe 1	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓	✓
	Mechanical kit for side card installation	Not included in F606 delivery											

- not supported by side card

✓ supported